SERVO LINEAR ACTUATOR

Kar-Tech's programmable servo linear actuator is designed to work retrofit or with any of Kar-Tech's on/off output, switch or joystick operated remote controls for actuation of valves, PTO, throttle and other mechanically actuated devices.

In retrofit applications outputs or switches can be used to step forward up to 30 user-programmable increments or proportional movement via joystick or potentiometer.

ANALOG DIGITAL

With a built in **GATE** Wifi Diagnostic, the actuator can easily be configured using a PC, Tablet or Smartphone for the mode of operation, inputs values, and the position of the shaft.

SOME AND A STATE AND A STATE AND A STATE AND A DAWAY A

Main Screen

KAR-TECH

RF Pc

Operates from 9 to 30 VDC and provides 90 pounds of force over a 3 inch stroke.

TECHNICAL INFO

| WEIGHT | 4.500000 | OPERATING TEMPERATURE | -40° to +85° C | STROKE (MAX) | 3.0" |
|--------|----------|-----------------------|-------------------|-----------------------------|-------------------|
| HEIGHT | 8.875" | HOUSING MATERIAL | Aluminum Die-Cast | OUTPUT FORCE (DYNAMIC) LOAD | 90 lb |
| WIDTH | 1.875" | INGRESS PROTECTION | IP65 | FEEDBACK | Contactless Sense |
| DEPTH | 4.00" | | | | |

